

Product Environmental Profile

Easy9 Compact Consumer Unit






General information

Representative product	Easy9 Compact Consumer Unit 6+6 split populated - EZ9ER6R6CMCCU
Description of the product	The Easy9 compact consumer unit is designed to control and distribute electrical energy, principally in domestic premises. It is compliant to BS7671:118th Edition Amendment No1 2020 and provides reliability, flexibility and efficiency.
Functional unit	Distribute electricity with assigned voltage 230/240VAC (Ue) and rated current 100A (In) during 20 years.



Constituent materials

Reference product mass	5530g including the product, its packaging and additional elements and accessories
------------------------	--



Plastics	10,4%
Metals	79,8%
Others	9,8%



Substance assessment

Products of this range are designed in conformity with the requirements of the RoHS directive (European Directive 2011/65/EU of 2 January 2013, amended in March 2015, 2015/863/EU and in November 2017, 2017/2102/EU) and do not contain, or only contain in the authorised proportions, lead, mercury, cadmium, hexavalent chromium or flame retardants (polybrominated biphenyls - PBB, polybrominated diphenyl ethers - PBDE), Bis (2-ethylhexyl)phthalate - DEHP, Benzyl butyl phthalate - BBP, Dibutyl phthalate - DBP, Diisobutyl phthalate - DIBP) as mentioned in the Directive.

Details of ROHS and REACH substances information are available on the Schneider-Electric Green Premium website

<http://www2.schneider-electric.com/sites/corporate/en/products-services/green-premium/green-premium.page>



Additional environmental information

The Easy9 Compact Consumer Unit 6+6 split populated presents the following relevant environmental aspects


Manufacturing	Manufactured at a Schneider Electric production site ISO14001 certified
Distribution	Weight and volume of the packaging optimized, based on the European Union's packaging directive Packaging weight is 530 g, consisting of Cardboard (96%), PE (2%), paper (2%) Product distribution optimised by setting up local distribution centres
Installation	The Easy9 compact consumer unit does not require any special installation operations. The disposal of the packaging materials are accounted during the installation phase (including transport to disposal).
Use	The product does not require special maintenance operations.
End of life	End of life optimized to decrease the amount of waste and allow recovery of the product components and materials No special end-of-life treatment required. According to countries' practices this product can enter the usual end-of-life treatment process. Recyclability potential: 84% Based on "ECO'DEEE recyclability and recoverability calculation method" (version V1, 20 Sep. 2008 presented to the French Agency for Environment and Energy Management: ADEME).



Environmental impacts

Reference life time	20 years			
Product category	Other equipments - Passive product - continuous operation			
Installation elements	The disposal of the packaging material is accounted for 9.7% during the installation phase.			
Use scenario	The consumer unit is operating 100% of the time for 20 years at 30A (30% of In)			
Geographical representativeness	United Kingdom			
Technological representativeness	The Easy9 compact consumer unit is designed to control and distribute electrical energy, principally in domestic premises. It is compliant to BS7671:118th Edition Amendment No1 2020 and provides reliability, flexibility and efficiency.			
Energy model used	Manufacturing	Installation	Use	End of life
	Energy model used: United Kindom	Electricity grid mix; AC; consumption mix, at consumer; 230V; GB	Electricity grid mix; AC; consumption mix, at consumer; 230V; GB	Electricity grid mix; AC; consumption mix, at consumer; 230V; GB

Compulsory indicators		Easy9 Compact Consumer Unit 6+6 split populated - EZ9ER6R6CMCCU					
Impact indicators	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Contribution to mineral resources depletion	kg Sb eq	2,21E-03	2,20E-03	0*	0*	7,07E-06	0*
Contribution to the soil and water acidification	kg SO ₂ eq	1,50E+00	9,43E-02	3,26E-03	0*	1,40E+00	1,43E-03
Contribution to water eutrophication	kg PO ₄ ³⁻ eq	1,54E-01	1,20E-02	7,50E-04	3,27E-05	1,41E-01	3,51E-04
Contribution to global warming	kg CO ₂ eq	4,58E+02	2,03E+01	7,13E-01	0*	4,36E+02	5,30E-01
Contribution to ozone layer depletion	kg CFC11 eq	5,75E-06	1,70E-06	1,45E-09	0*	4,02E-06	3,04E-08
Contribution to photochemical oxidation	kg C ₂ H ₄ eq	8,62E-02	8,10E-03	2,32E-04	9,08E-06	7,77E-02	1,54E-04
Resources use	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Net use of freshwater	m3	9,80E+01	3,11E-01	0*	0*	9,77E+01	0*
Total Primary Energy	MJ	7,64E+03	5,05E+02	1,01E+01	0*	7,12E+03	7,17E+00



Optional indicators		Easy9 Compact Consumer Unit 6+6 split populated - EZ9ER6R6CMCCU					
Impact indicators	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Contribution to fossil resources depletion	MJ	5,71E+03	1,78E+02	1,00E+01	0*	5,51E+03	5,75E+00
Contribution to air pollution	m³	3,31E+04	7,13E+03	3,04E+01	0*	2,59E+04	5,09E+01
Contribution to water pollution	m³	1,65E+04	2,59E+03	1,17E+02	4,39E+00	1,38E+04	5,59E+01
Resources use	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Use of secondary material	kg	1,45E+00	1,45E+00	0*	0*	0*	0*
Total use of renewable primary energy resources	MJ	3,39E+02	9,16E+00	0*	0*	3,30E+02	0*
Total use of non-renewable primary energy resources	MJ	7,30E+03	4,96E+02	1,01E+01	0*	6,79E+03	7,16E+00
Use of renewable primary energy excluding renewable primary energy used as raw material	MJ	3,29E+02	0*	0*	0*	3,30E+02	0*
Use of renewable primary energy resources used as raw material	MJ	1,01E+01	1,01E+01	0*	0*	0*	0*
Use of non renewable primary energy excluding non renewable primary energy used as raw material	MJ	7,29E+03	4,82E+02	1,01E+01	0*	6,79E+03	7,16E+00
Use of non renewable primary energy resources used as raw material	MJ	1,43E+01	1,43E+01	0*	0*	0*	0*
Use of non renewable secondary fuels	MJ	0,00E+00	0*	0*	0*	0*	0*
Use of renewable secondary fuels	MJ	0,00E+00	0*	0*	0*	0*	0*
Waste categories	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Hazardous waste disposed	kg	1,33E+02	1,27E+02	0*	0*	1,13E-01	5,75E+00
Non hazardous waste disposed	kg	6,65E+02	1,90E+01	0*	0*	6,46E+02	0*
Radioactive waste disposed	kg	5,30E-01	3,60E-03	0*	0*	5,26E-01	0*
Other environmental information	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Materials for recycling	kg	5,20E+00	5,39E-01	0*	5,20E-01	0*	4,14E+00
Components for reuse	kg	0,00E+00	0*	0*	0*	0*	0*
Materials for energy recovery	kg	2,30E-02	0*	0*	0*	0*	2,30E-02
Exported Energy	MJ	1,64E-03	1,54E-04	0*	1,49E-03	0*	0*



* represents less than 0.01% of the total life cycle of the reference flow

Life cycle assessment performed with EIME version EIME v5.9.1, database version 2016-11 in compliance with ISO14044.

The use phase is the life cycle phase which has the greatest impact on the majority of environmental indicators (based on compulsory indicators).

Please note that the values given above are only valid within the context specified and cannot be used directly to draw up the environmental assessment of an installation.

Registration number :	SCHN-00657-V01.01-EN	Drafting rules	PCR-ed3-EN-2015 04 02
Verifier accreditation N°	VH39	Supplemented by	PSR-0005-ed2-EN-2016 03 29
Date of issue	03/2021	Information and reference documents	www.pep-ecopassport.org
		Validity period	5 years
Independent verification of the declaration and data, in compliance with ISO 14025 : 2010			
Internal	External	X	
The PCR review was conducted by a panel of experts chaired by Philippe Osset (SOLINNEN)			
PEP are compliant with XP C08-100-1 :2016			
The elements of the present PEP cannot be compared with elements from another program.			
Document in compliance with ISO 14025 : 2010 « Environmental labels and declarations. Type III environmental declarations »			





Schneider Electric Industries SAS

Country Customer Care Center
<http://www.schneider-electric.com/contact>

35, rue Joseph Monier
 CS 30323
 F- 92506 Rueil Malmaison Cedex
 RCS Nanterre 954 503 439
 Capital social 896 313 776 €

www.schneider-electric.com

Published by Schneider Electric

SCHN-00657-V01.01-EN

© 2019 - Schneider Electric – All rights reserved

03/2021